





Forward to	Sender	GPU information
AXA Power	Company :	Type :
Fax + 45 63 18 60 49	Fax :	Serial No. :
Phone + 45 63 18 60 00	Phone :	Error Code :     /     /
Mail : service@axapower.com	Contact :	<b>Please always state serial no.</b>
	E-mail :	

**How to get access to the black box :**

1. Press  and  at the same time and you get access to the black box.

2. By means of the arrow keys, go to error code no. : \_\_\_\_\_ / \_\_\_\_\_ / \_\_\_\_\_

3. Press 

4. Press  and read out the following information :

<b>Input voltage</b>	L1-L2 :	V	L2-L3 :	V	L3-L1 :	V
<b>Input frequency</b>		Hz				
<b>Voltage at DC capacitor bank</b>	Delta :	V	Instant:	V	Avg. :	V
<b>Output current</b>	Ph A :	A	Ph B :	A	Ph C :	A
<b>Inverter current</b>	Ph A :	A	Ph B :	A	Ph C :	A
<b>Output voltage phase-neutral</b>	A-N :	V	B-N :	V	C-N :	V
<b>Module temp.</b>	DC :	C°	AC1 :	C°	AC2 :	C°
<b>Internal DC volt.</b>	-5V :	V	12 V :	V	17 V :	V
<b>Setup values</b>	Voltage :	V	Compensation :	V	Amp. :	A

**Other indication (lamps, LED's, damages of enclosure etc.) :**

**Remarks :**