





<b>Forward to</b>  AXA Power Fax + 45 63 18 60 49 Phone + 45 63 18 60 00 Mail : service@axapower.com	<b>Sender</b>	<b>AXA Twin Power GPU information</b>
	Company :	Type :
	Fax :	Serial No. :
	Phone :	Error Code :     /     /
	Contact :	<b>Please always state serial no.</b>
E-mail :		

**How to get access to the black box :**

1. Press  and  at the same time and you get access to the black box.
2. By means of the arrow keys, go to error code no. : \_\_\_\_\_ / \_\_\_\_\_ / \_\_\_\_\_
3. Press 
4. Press  and read out the following information :

<b>Altonator voltage</b>	L1-L2 :	V	L2-L3 :	V	L3-L1 :	V
<b>Altonator frequency</b>		Hz				
<b>Voltage at DC capacitor bank</b>	Instant:	V	Avg. :	V		
<b>Output current</b>	Ph A :	A	Ph B :	A	Ph C :	A
<b>Inverter current</b>	Ph A :	A	Ph B :	A	Ph C :	A
<b>Output voltage phase-neutral</b>	A-N :	V	B-N :	V	C-N :	V
<b>Internal DC volt.</b>	-5V :     V	12 V :	V	17 V :	V	30 V :     V
<b>Setup values</b>	Voltage		V	Compensation		V
<b>Battery voltage</b>	V		<b>Charge voltage</b>	V		
<b>Engine temperatire</b>	°C		<b>Oil pressure</b>	BAR		
<b>Can Status EMR</b>						
<b>Engin. speed EMR</b>	rpm		<b>Engine torque</b>	%		
<b>Fuel level</b>	/8		<b>Fuel rate</b>	[L/h]		

Other indications (lamps, LEDs, damages of enclosure etc.) :

Remarks :

Spare parts are available from [www.axapower.com](http://www.axapower.com)